



VMS Software

TIMEZONE V1.0 ECO Kit for VSI OpenVMS x86-64

Release Notes

Publication Date: October 2026

Operating System: VSI OpenVMS x86-64 V9.2-3

Kit Name: VMS923X_TIMEZONE-V0100

Table of Contents

1. Kit Name	3
2. Kit Description	3
2.1. Installation Rating	3
2.2. Reboot Requirement	3
2.3. Version(s) of VSI OpenVMS to Which This Kit May Be Applied	3
3. Kits Superseded by This Kit	3
4. Kit Dependencies	4
5. Problems Addressed in This Kit	4
5.1. Daylight Savings Time Update for Several Canadian Provinces	4
6. Problems Addressed From Previous Kits	5
7. Images or Files Replaced	5
8. Installation Instructions	6
8.1. Compressed File	6
8.2. Installation Command	7
8.3. Special Installation Instructions	7
9. Copyright	7
10. Disclaimer of Warranty and Limitation of Liability	8
11. Patch ID	8
Appendix A. User-Selectable Control Options and Scripting Considerations	8
A.1. Controlling Kit Behavior for Introductory Questions	8
A.2. Standard Behavior for YES/NO Questions Asked During Kit Installation	9
A.3. Installing a Kit From a Batch Job	10
A.4. Deprecated Logical Names From HPE ECO Kits	10

1. Kit Name

VMS923X_TIMEZONE-V0100

2. Kit Description

2.1. Installation Rating

INSTALL_3: To be installed by customers experiencing the problems described in this document.

This installation rating serves as a guide to which customers should apply this remedial kit.

This kit updates the time zone rules for the following Canadian provinces: British Columbia, the Northwest Territories, Alberta, and Manitoba, which are located in the Pacific, Mountain, and Central time zones. The time zone rules have been changed to make the current offset for UTC time permanent.

If your system is in one of these provinces you should apply this ECO kit.

If your system is not in any of these Canadian provinces, you do not need to install this ECO kit.

Reference the [Disclaimer of Warranty and Limitation of Liability Statement](#).

2.2. Reboot Requirement

A reboot is required after installing this kit. See [Special Installation Instructions](#) for details about kit installation and rebooting.

VMS Software, Inc. strongly recommends that a reboot be performed immediately after kit installation to avoid system instability.

If you are installing this kit in an OpenVMS cluster, any systems that share the same system disk with the installing system must also be rebooted in order to make use of the new images.

2.3. Version(s) of VSI OpenVMS to Which This Kit May Be Applied

VSI OpenVMS x86-64 V9.2-3

Attention

The TIMEZONE V1.0 ECO kit is not supported on VSI OpenVMS x86-64 V9.2-2.

3. Kits Superseded by This Kit

None.

4. Kit Dependencies

VMS923X_PCSI-V0100

Note

This kit must be installed separately before installing the TIMEZONE V1.0 ECO kit. It may not be installed simultaneously using the same **PRODUCT INSTALL** command.

5. Problems Addressed in This Kit

5.1. Daylight Savings Time Update for Several Canadian Provinces

Problem Description

The Canadian provinces of Alberta, British Columbia, the Northwest Territories, and Manitoba have changed their Daylight Savings Time rules to keep the current system time offset permanent.

This means that the Daylight Savings Time rules specify that the time offset stays the same, with no plus or minus one hour any longer.

The kit only affects the rules for the Canadian time zone used for those provinces: Central, Pacific, and Mountain.

Images and/or Files Affected

```
[SYS$ZONEINFO.SYSTEM.SOURCES]NORTHAMERICA.  
[SYS$ZONEINFO.SYSTEM.AMERICA]EDMONTON.  
[SYS$ZONEINFO.SYSTEM.AMERICA]INUVIK.  
[SYS$ZONEINFO.SYSTEM.AMERICA]VANCOUVER.  
[SYS$ZONEINFO.SYSTEM.AMERICA]WINNIPEG.  
[SYS$ZONEINFO.SYSTEM.CANADA]CENTRAL.  
[SYS$ZONEINFO.SYSTEM.CANADA]MOUNTAIN.  
[SYS$ZONEINFO.SYSTEM.CANADA]PACIFIC.
```

VSI Case Identifier

Jira RTLS-582
Netsuite NS9456

Release Version of VSI OpenVMS That Will Contain This Change

Next VSI OpenVMS x86-64 release after V9.2-3

Workaround

To avoid accidental system clock change when daylight savings time is enabled or disabled, set the system parameter `AUTO_DLIGHT_SAV` to 0 in the active set of system parameters.

```
$ RUN SYS$SYSTEM:SYSGEN
```

```
SYSGEN>  USE  ACTIVE
SYSGEN>  SET  AUTO_DLIGHT_SAV 0
SYSGEN>  WRITE ACTIVE
```

To make this a permanent change, be sure to update SYSS\$SYSTEM:MODPARAMS.DAT and run AUTOGEN to set the permanent parameters to use on reboot.

6. Problems Addressed From Previous Kits

None.

7. Images or Files Replaced

[SYSS\$ZONEINFO.SYSTEM.SOURCES]NORTHAMERICA.

File Creation Date and Time:	25-SEP-2026 18:53:40.00
Checksum (MD5):	7163B6CCEF2AD9ECCC8B36D654F349CA

[SYSS\$ZONEINFO.SYSTEM.AMERICA]EDMONTON.

File Creation Date and Time:	4-OCT-2026 05:03:49.42
Checksum (MD5):	4E032BA3CD13C0C252B58D652B7685D1

[SYSS\$ZONEINFO.SYSTEM.AMERICA]INUVIK.

File Creation Date and Time:	4-OCT-2026 05:03:49.48
Checksum (MD5):	EA5734F5E15BF411A9025AE7A54AB372

[SYSS\$ZONEINFO.SYSTEM.AMERICA]VANCOUVER.

File Creation Date and Time:	4-OCT-2026 05:03:49.43
Checksum (MD5):	1928A6F61808F5E08900EAC0A18A8C67

[SYSS\$ZONEINFO.SYSTEM.AMERICA]WINNIPEG.

File Creation Date and Time:	4-OCT-2026 05:03:49.40
Checksum (MD5):	B1495A7F71159C97B5E0E9BA49D3B140

[SYSS\$ZONEINFO.SYSTEM.CANADA]CENTRAL.

File Creation Date and Time:	4-OCT-2026 21:32:59.42
Checksum (MD5):	B1495A7F71159C97B5E0E9BA49D3B140

[SYSS\$ZONEINFO.SYSTEM.CANADA]MOUNTAIN.

File Creation Date and Time:	4-OCT-2026 21:32:59.43
------------------------------	------------------------

Checksum (MD5):	4E032BA3CD13C0C252B58D652B7685D1
-----------------	----------------------------------

[SYSS\$ZONEINFO.SYSTEM.CANADA]PACIFIC.

File Creation Date and Time:	4-OCT-2026 21:32:59.43
Checksum (MD5):	1928A6F61808F5E08900EAC0A18A8C67

Note

VMS Software, Inc. will only distribute kits in signed form. There is no need for most customers to compare file checksums for security or kit integrity reasons.

However, some sites may require such checking even when using signed kits. The image or file checksums (in MD5 format) are supplied to provide comparisons to the extracted final kit files. To find a file checksum, use:

```
$ CHECKSUM/ALGORITHM=MD5 filename
$ SHOW SYMBOL CHECKSUM$CHECKSUM
```

Note

Because a file or image may be replaced by multiple ECO kits over time, a PCSI generation number is used to ensure that the latest version of the file or image is preserved on your system during **PRODUCT INSTALL** of an ECO kit. Should a particular kit installation discover a newer version of a file or image in place on the system disk, the following message will be displayed:

```
%PCSI-I-RETAIN, file filename will not be replaced because file from kit
has lower generation number
```

This is a normal occurrence depending on the order of kit installation. The correct version of the file or image will remain on the system after the current kit installation. The %PCSI-I-RETAIN message is informational only and does not indicate a problem.

8. Installation Instructions

8.1. Compressed File

This kit is provided for download within a ZIP archive container file.

Info-ZIP's freeware ZIP and UNZIP tools are provided for use on this VSI OpenVMS version. Your site may have already set up symbols for these tools or other equivalent ZIP tools. If not, use the following command to define a symbol to run the UNZIP image:

```
$ UNZIP :== "$SYSS$SYSDEVICE:[VMS$COMMON.SYSHLP.UNSUPPORTED.UNZIP]UNZIP"
```

Then invoke UNZIP to unpack the kit using the command:

```
$ UNZIP VMS923X_TIMEZONE-V0100
```

This will extract the installable PCSI product kit file and its associated signed manifest (_VNC file), used for kit validation during **PRODUCT** commands.

VSI strongly recommends always using the manifest to validate the kit content during any **PRODUCT** commands. This will occur automatically if the files are both contained in the same directory.

8.2. Installation Command

Install this kit with the POLYCENTER Software Installation Utility by logging into the SYSTEM account and typing the following command at the DCL prompt:

```
$ PRODUCT INSTALL VMS923X_TIMEZONE [/SOURCE=location_of_kit]
```

The kit location may be a CD/DVD or a disk directory that contains the kit. The **/SOURCE** qualifier is not needed if the **PRODUCT INSTALL** command is executed from the same directory as the kit location.

This kit requires the use of **/RECOVERY_MODE** and **/SAVE_RECOVERY_DATA** and will automatically set them; they do not need to be present on the command line.

The release notes for any kit may be extracted prior to kit installation using the **PRODUCT EXTRACT RELEASE_NOTES** command.

User-selectable options for installation behavior and scripting are available in this kit, refer to *Appendix A, "User-Selectable Control Options and Scripting Considerations"* for further details.

Additional help on installing PCSI kits can be found by typing **HELP PRODUCT INSTALL** at the system prompt.

8.3. Special Installation Instructions

After installing this kit, you must update the time zone rule in use on the system. Use the command:

```
$ @SYS$MANAGER:UTC$TIME_SETUP
```

If your system is using DTSS, you should use NET\$CONFIGURE or the corresponding DCE procedure to make time zone and time differential changes.

After kit installation and updating the time zone rule, VSI strongly recommends rebooting the system to:

1. Ensure that the correct time zone rules are used at system startup.
2. Ensure that any cached copy of the old time zone rule is no longer used by any applications or servers. The C RTL caches the time zone information on behalf of the image that first requested it, and restarting the process or rebooting the system are the only ways to ensure the new rule is used.

If your system shares a common system disk with other nodes in a VMSccluster, the same steps should be taken on those nodes to ensure the new rule is used.

9. Copyright

VMS SOFTWARE, INC. CONFIDENTIAL. This software is confidential proprietary software licensed by VMS Software, Inc., and is not authorized to be used, duplicated, or disclosed to anyone without the prior written permission of VMS Software, Inc.

Copyright 2026 VMS Software, Inc.

10. Disclaimer of Warranty and Limitation of Liability

This patch is provided as is, without warranty of any kind. All express or implied conditions, representations, and warranties, including any implied warranty of merchantability, fitness for particular purpose, or non-infringement, are hereby excluded to the extent permitted by applicable law. In no event will VMS Software, Inc. be liable for any lost revenue or profit, or for special, indirect, consequential, incidental or punitive damages, however caused and regardless of the theory of liability, with respect to any patch made available here or to the use of such patch.

11. Patch ID

X86VMS-VMS923X_TIMEZONE-V0100--4

Note

The terms "ECO kit" and "patch kit" may be used interchangeably in this document. This also applies for other VSI OpenVMS documentation when describing PCSI kits that provide remedial updates to a particular product.

A. User-Selectable Control Options and Scripting Considerations

A.1. Controlling Kit Behavior for Introductory Questions

This kit provides user-selectable control options for kit dialogue interaction and automated scripting capability as described here in this appendix.

The general form of a VSI OpenVMS ECO kit, when using **PRODUCT INSTALL**, consists of three initial questions regarding these topics:

1. System disk backup: A reminder that VSI recommends backing up the system disk before installing updates, followed by a `Do you want to continue? YES/NO` question, default is YES.
2. Reboot requirement: A summary of whether the kit being installed requires a system reboot, followed by a `Do you want to continue? YES/NO` question, default is YES.
3. Archival of updated files: A description of saving an `"_OLD"` copy of each image or file updated by the kit, followed by a `Do you want to save "_OLD" copies of replaced files? YES/NO` question, default is NO.

Other questions may be asked later, depending on the target disk or system environment or other kit-specific requirements.

Note

An initial `Do you want to continue?` question may be asked directly by the PCSI utility during any **PRODUCT** command – this has nothing to do with the kit being used. To avoid that

question, you must supply sufficient detail to uniquely identify the product you wish to use and specify **/OPTIONS=NOCONFIRM** on the **PRODUCT** command.

Control options are available to customize the dialogue for the initial three kit questions. The controls are logical names, which may be defined in the process logical name table with a value of YES or NO.

To modify the behavior of a VSI OpenVMS ECO kit regarding the initial questions, define one or more of the following logical names before issuing the **PRODUCT INSTALL** command.

- To skip one or more of the questions, define the corresponding logical name shown here to YES:

SKIP\$BACKUP	Skips system backup awareness question.
SKIP\$REBOOT	Skips system reboot awareness question.
SKIP\$ARCHIVE_OLD	Skips question about saving "_OLD" files. This will take the default, which is NO.
SKIP\$INTRO	Skips all three of the above questions.

- To specifically override the default for saving "_OLD" files, define this logical name to YES or NO:

VSIKIT\$ARCHIVE_OLD	Sets an answer for saving "_OLD" files behavior. This will skip the archive "_OLD" files question regardless of the above SKIP\$* logical names.
---------------------	--

- Two additional logical names may be defined as YES to modify the amount of explanatory text displayed for each question:

VSIKIT\$VERBOSE	Shows all explanatory text for questions.
VSIKIT\$BRIEF	Skips some general details in the explanations.

The default if neither name is defined is VERBOSE. If both names are defined to YES, VERBOSE overrides BRIEF. The BRIEF form is displayed for any questions that are skipped.

For example, to skip all three questions but save an archive "_OLD" copy of each replaced file:

```
$ DEFINE VSIKIT$ARCHIVE_OLD YES
$ DEFINE SKIP$INTRO YES
$ PRODUCT INSTALL kitname
```

A.2. Standard Behavior for YES/NO Questions Asked During Kit Installation

Any YES/NO questions asked during kit installation now follow these rules:

1. **Ctrl/Y** issued while a question is being asked will force the current **PRODUCT** operation to terminate. This is completely safe to do while the initial three questions are being asked during **PRODUCT INSTALL** as no changes have yet been made to the target disk.
2. Some questions may ignore **Ctrl/Y** and ask for a specific answer (for example, if aborting the current operation may have side effects for the system). Additionally, note the following:
 - PCSI may trap **Ctrl/Y** directly for some **PRODUCT** operations.

- **Ctrl/Y** may be disabled during some sensitive kit processing.
3. The default YES/NO answer is automatically chosen if a kit is installed from a batch job, unless explicitly overridden by a logical name that provides the particular value, such as `VSIKIT$ARCHIVE_OLD`.

A.3. Installing a Kit From a Batch Job

To install a kit from a batch job, you will need to fully qualify the kit name so PCSI will have enough information to select the kit without asking for confirmation. For example, to install this kit:

```
$ PRODUCT INSTALL VMS923X_TIMEZONE/VERSION=V1.0/OPTIONS=NOCONFIRM
```

If the kit is located in a directory other than the current default directory, you will also need to add the qualifier:

```
/SOURCE=location_of_the_kit
```

For a batch job, any YES/NO question will automatically select the default answer. Use the control logical names explained above to modify the behavior if necessary. For the system disk backup and reboot questions, the batch behavior is identical to the default. For the save "_OLD" files question, define the `VSIKIT$ARCHIVE_OLD` logical name to YES if you want to save copies of the files, since the batch default is NO.

A.4. Deprecated Logical Names From HPE ECO Kits

The three names listed below were used by older VSI OpenVMS ECO kits for compatibility with HPE ECO kit behavior. These old names continue to function, but VSI encourages you to modify any scripts you may have to use the new names shown instead:

Old Name	New Name
NO_ASK\$BACKUP	SKIP\$BACKUP
NO_ASK\$REBOOT	SKIP\$REBOOT
ARCHIVE_OLD	VSIKIT\$ARCHIVE_OLD